

Product datasheet

Specifications



potentiometer -10000 Ohm - for XKB XKD XKM

XKZA15100

Main

Product or component type	Controllers separate parts
Accessory / separate part category	Control accessories
Product specific application	Medium hoisting applications Heavy hoisting applications Light hoisting applications
Product compatibility	XKB XKD XKM
Accessory / separate part type	Potentiometer
Condition of use	For standard applications
Ohmic value	10000 Ohm
Size	15 mm

Complementary

Standards	UTE 93-265
Potentiometer characteristic	Linear function Continuous rotational operation
Operating angle	360 °
Mechanical durability	3000000 cycles
Centre tap	Wired out to terminal
Centre tap dead zone	2 ° +/- 1 %
Power dissipation in W	3 W 85 °C
Connections - terminals	Flying leads from soldered standard tags
Net weight	0.06 kg

Environment

Mounting mode	By the body
---------------	-------------

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	4.4 cm
Package 1 Width	6.2 cm
Package 1 Length	5.4 cm

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Package 1 Weight	66 g
Unit Type of Package 2	S01
Number of Units in Package 2	24
Package 2 Height	15 cm
Package 2 Width	15 cm
Package 2 Length	40 cm
Package 2 Weight	1.782 kg

Contractual warranty

Warranty	12 months
----------	-----------



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better



Materials and Substances

[EU RoHS Directive](#)

Pro-active compliance (Product out of EU RoHS legal scope)

Use Again



Repack and remanufacture

WEEE



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins